

## AS-1000

The ANY SPOT (AS-1000) is the new wireless in ear monitor from Galaxy Audio. Galaxy Audio has been manufacturing the HOT SPOT personal monitor for 30 years. The ANY SPOT is the latest monitor from the 'Monitor Guys'. Wireless personal monitors are effective at eliminating stage noise, protecting users ears from damage, allowing the user to move around a stage or audience and continue to hear, and eliminate feedback.

The ANY SPOT is easy to use. The ANY SPOT replaces floor wedges and the amplifiers that power them. Simply plug the ANY SPOT into a 'monitor out' jack on a mixing console, create the desired mix, and it's ready to deliver quality sound. The ANY SPOT has 64 selectable UHF frequencies to help locate the best and clearest one to transmit signal. The transmitter (AS-1000T) is selectable to either mono or stereo.

The ANY SPOT AS-1000 features a diversity receiver. Our diversity receiver (AS-1000R) has two antennas. Each antenna seeks the signal from the transmitter individually. This means fewer dropouts than a non-diversity system. In the rare event of a dropout, our 'Auto-Mute' feature kicks in. Auto-Mute prevents intermittent static from going into the users ears.

The ANY SPOT is also a great assistive listening system. The AS-1000T will transmit to numerous receivers. Simply patch the program signal to the transmitter and give each parishioner or attendee a receiver so all can hear clearly.



The ANY SPOT transmitter has RCA, XLR, & ¼" inputs on the back. The ANY SPOT allows simultaneous broadcast of audio signals from a source such as a CD player, tape player, computer, IPod, etc, and a microphone while offering individual level adjustment for each of the two sources. This works great for presentations or a solo performer who wants to monitor a microphone and backing track.

The ANY SPOT is a great alternative for performers who are tired of lugging around heavy and bulky floor monitors and tired of leaving a gig with ringing ears. The ANY SPOT allows the user to move freely around the stage or audience and continue to hear the monitor mix. The ANY SPOT package is also lighter in weight than floor monitors, which makes it easier to transport from location to location.

The ANY SPOT is cost competitive and feature packed and is a great buy for any church or band. One year warranty



## System Specifications

AS-1000R Receiver	
Carrier Frequency Range	UHF band 682~698 MHz. 64 CH
Oscillator	PLL synthesized
Modulation	FM
Receiving Mode	Single channel. Diversity
Frequency Stability	±0.005%
S/N ratio	>94dB, at 15KHz deviation and
	60dBuV antenna input
Power Supply	DC 3V (2 x 1.5V AA batteries or
	rechargeable batteries)
Image and Spurious Rejection	80 dB minimum
Receiving Sensitivity	At 5 dBµV over 80 dB S/N ratio
Selectivity	>50dB
AF Response	Headphone: 100Hz to 10KHz (±3dB)
	Line: 40Hz to 15KHz (±3dB)
T.H.D.	<1% (at 1KHz)
IF Frequency	1 <sup>st</sup> 56MHz; 2 <sup>nd</sup> 10.7MHz
Dynamic Range	>96dB
Audio Output	Headphone stereo output: 20mW,
	Line stereo output level: -10dB
Current Consumption	130mA ± 10mA
Case	Bodypack
Dimension W x H x D	3" x 4.2" x 1.2" (76 x 106 x 29mm)

AS-1000T Transmitter	
Frequency Range	UHF 682~698MHz
Frequency Stability	±0.005%
Maximum Deviation	±48KHz with limiting compressor
Power Supply	DC 12 ~18V
Spurious Emission	>60dB below carrier frequency
RF Power Output	100mW
T.H.D.	<1% (at 1KHz)
Tone Key	32.768KHz
Current Consumption	140mA ± 10mA (100mV)
Dimension W x H x D	3" x 4.2" x 1.2" (76 x 106 x 29mm)

	ANY SPOT	ACCESSORIES
	AS-CASE1000	ANY SPOT CASE FOR MICS Holds 1 AS-1000T, 1 AS-1000R, AS-DCC and many accessories. Dimensions: 17.5" x 14.5" x 4" 4.5lbs
	AS-DCC	DC CHARGER DC charger will charge up to 5 AS-1000R's or other DC chargeable units from Galaxy including AS-MBP5, AS-MBP7, AS-HH5 & AS-HH7. 5 charging cables included.
	AS-LRE	LONG RACK EARS long rack ears will mount any single Any Spot rack unit into one rack space
000	AS-SRE	SHORT RACK EARS short rack ears will mount and two Any Spot rack units into two rack space; connecting plate included.
	AS-EB2	EAR BUD Ear bud comes standard with the AS-1000. Includes extra set of foam sleeves. Utilizes 4' cord and stereo 3.5mm plug
	AS-EC1	FIXED EAR CUP-BLACK Ear cup wraps around ear. Utilizes 4' cord and stereo 3.5mm plug
	AS-EC2	RUBBER EAR CUP-BLUE Ear cup has a rubber wrap for a more comfortable fit around the ear. Utilizes 4' cord and stereo 3.5mm plug
4	AS-EC3	OVER EAR CUP Ear cup wraps over and around the ear. Utilizes 4' cord and stereo 3.5mm plug

Specifications subject to change without notice.



MAKERS OF THE ORIGINAL HOT SPOT PERSONAL MONITOR

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com Distributed outside the United States by E and E Exports, Inc. 2815 Junipero Ave. Suite 101Signal Hill, CA 92614 562.988.3447 FAX 562.989.3037 Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada 450.449.8177 FAX 450.449.8180