



[www.galaxyaudio.com](http://www.galaxyaudio.com)

### **THREE YEAR LIMITED WARRANTY**

WARRANTY Information can be viewed online at  
<https://www.galaxyaudio.com/support/warranty>



[www.galaxyaudio.com/support/warranty](http://www.galaxyaudio.com/support/warranty)

# **GT-INST-3**

1-800-369-7768 [www.galaxyaudio.com](http://www.galaxyaudio.com)

Specifications in this manual are subject to change without notice.

© Copyright Galaxy Audio 2019

Printed in China

V20190415

## **GT-INST-3** Horn Mic System

# **USER'S MANUAL**



**MAKERS OF THE ORIGINAL  
HOT SPOT PERSONAL MONITOR**

## GT-INST-3

## Instructions

1. Put the receiver into the 1/8" (3.5 mm) Mic input of an amplifier, powered speaker, or other audio device or use the included 1/4" (6.5 mm) adapter for 1/4" inputs. For Apple or Android phones, use the included phone adapter cables.



2. Slide the transmitter onto the horn mic, and clip the horn mic onto a horn instrument.



3. On the Receiver, move the Power switch to On. The LED will begin flashing.



4. On the Transmitter, move the Power switch to On. The LED will briefly flash until the Transmitter and Receiver automatically pair. The LED will then remain on.



5. Adjust the volume to a suitable level. It is ready for use.



## Caution

The LED will turn red when power is low, and will turn off when less than 10%. The LED will also turn red when charging.

Store in a dry location away from moisture. Avoid excessive heat.

For repair services, please contact Galaxy Audio. Do not attempt open or repair it. Doing so will void warranty.

## Receiver



## Transmitter

**System Specifications:**

Frequency Range: 2.4GHz Frequency Hopping  
Frequency Response: 20Hz-20KHz  
Pairing: Auto-Match

**Horn Microphone:**

Mic Diameter: 0.24" x 0.55" (6.5 x 14 mm) (LxDia.)  
Polar Pattern: Uni-Directional  
Sensitivity: -47dB ±2dB  
Frequency Response: 40Hz - 16kHz  
Standard Operating Voltage: 2.0V - 10V.DC  
Signal to Noise Ratio: >63dB  
Impedance: ≤680Ω

**Transmitter:**

Controls: On-Off Power Switch, Volume Control  
Battery: Lithium-Ion Rechargeable  
Input: Mini USB Charging  
Indicators: Power and Pairing LED

**Receiver:**

Controls: On-Off Power switch  
Battery: Lithium Ion  
Input: Mini USB charging  
Output: 3.5mm stereo output plug  
Indicators: Power and Pairing LED

**Included Accessories:**

Cell Phone Adapter Cables (Red for most Android, Black for most Apple)  
1/8 inch to 1/4 inch Adapter  
USB Charging Cable  
19.7 inch Female to Male Extension Cable  
Windscreen

