

The VSC System makes diversity wireless microphones available to everyone. With dual telescopic antennas, the rugged plastic housing of the VSCR receiver will endure the practice room, or the stage. The 1/4" output connects easily to any mixer board, and the front mounted volume allows for easy adjustment in the middle of the performance. The VSCR Receiver has LED Power, RF, and Audio indicators on the front, as well as a squelch adjustment on the rear of the unit.

The HH18 handheld and the MBP18 body pack feature silent on/off switches and run off two AA batteries. Standard battery life is about 8 hours. The MBP18 body pack also features a 1/8" threaded input connector and will work with any of Galaxy Audio's wireless headsets or lavalieres.

The VSC Triple Play system includes the VSCR receiver, the MBP18 body pack, a headset, lavalier, and a guitar cable. The VSC handheld system includes the VSCR receiver and the HH18 handheld.

The VSC wireless is a fixed frequency system with frequencies available from 173-174 MHz.



VSC OPTIONS

HANDHELD

VSCR/
H18



VSCR/
318



ANY SPOT

WIRELESS MICROPHONE SYSTEMS

VSC SERIES

VSCR Receiver

- RF & Audio Indicators
- Frequency Response: 60Hz-16kHz
- Unbalanced 1/4" Output
- Diversity Telescopic Antennas
- Dimensions: 1.73" x 9.25" x 4.6"
(44mm H x 235mm W x 118mm D)
- Weight: 11.2oz (318grams)

Frequencies:

CODE V54 173.8 MHz

CODE V59 174.1MHz

CODE V60 174.5MHz

CODE V61 174.8MHz



VSCR



VSCR- backview

HH18 Handheld

- VHF
- On/Off Switch
- Dynamic Cardioid Element
- Runs on 2-AA Batteries (about 8 hours)
- Dimensions: 2" x 9.6" (49mm x 245mm)
- Weight: 8.01oz (227grams)



HH18

MBP18 Body Pack

- VHF
- On/Off/Standby Switch
- Mic/Line Switch
- Runs on 2-AA Batteries (about 8 hours)
- Dimensions: 4.14" x 2.6" x 0.91"
(105mm H x 65mm W x 23mm D)
- Weight: 2.7oz (77grams)



MBP18



top view



MAKERS OF THE ORIGINAL
HOT SPOT PERSONAL MONITOR

Specifications subject to change without notice.

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com

Distributed outside the United States by E and E Exports, Inc. 2815 Junipero Ave. Suite 101 Signal Hill, CA 92614
562.988.3447 FAX 562.989.3037

Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada
450.449.8177 FAX 450.449.8180

V07182012